

## 90si User's Guide Addendum for the Model 390 Secure Fax System (MFC-7225N and 90si)



Set up your MFC-7225N and your 90si per the directions in the **Easy-Fax 90si Secure Facsimile Gateway User's Guide** detailed in **Section 2.0 Installation**.

### Setting the MFC-7225N's Ring Delay to "00"

1. If the "Fax" button is not illuminated green, press the "Fax" button
  2. Press "Menu/Set", "2", "1", "1" the display will read "1.Ring Delay" and then "Ring Delay:04"
  3. Press the down-arrow button until the display reads "Ring Delay:00"
  4. Press "Menu/Set"
  5. Press "Stop/Exit"
- (see the Brother MFC-7225N "User's Guide" pages 4-1 & 4-2 for more info)

### 90si User's Guide Changes

The following 90si User's Guide sections, 3.3 and 3.4, have been modified specifically for the MFC-7225N. All other sections of the 90si User's and Reference Guides remain unchanged.

#### 3.3 Sending a Secure Facsimile

1. Place a call on your Secure Telephone (STE, OMNI or STU-III)
2. Place your Secure Telephone in Secure Data mode
3. Insure that the "Fax" button is illuminated green. If not, press it and Load your document on the MFC-7225N face down
4. Press "Hook/Hold" then "1" on the dial pad and then "Start"
5. Standby while the document is transmitted. The fax will beep once (and return to the idle "time, date and Fax" display) when it is done indicating that it is OK to return to secure-voice, clear-voice mode or terminate the call.



GateWay  
Fax  
Systems, Inc.

GateWay Fax Systems, Inc.  
Virginia, USA  
Toll Free: 1-877-951-9800  
Tel: 804-796-1900, Fax: 804-796-1116  
Web: <http://www.gwfs.com>  
Email: [info@gwfs.com](mailto:info@gwfs.com)

### 3.4 Receiving a Secure Facsimile

Note: Insure that your MFC-7225N has "Fax" in the display when idle. This indicates that the fax is in Auto-Receive mode. If it does not, press "Menu/Set", "0", "1" then press the up or down-arrow button until the display reads "Fax Only" then press "Menu/Set" and "Stop/Exit." The idle display will then change to display the date, time and "Fax."

1. Answer your Secure Telephone (STE, OMNI or STU-III)
2. Place your Secure Telephone in Secure Data mode. The sender usually does this.
3. Standby, the fax will be received automatically. The fax will beep once (and return to the idle "time, date and Fax" display) when it is done indicating that it is OK to return to secure-voice, clear-voice mode or terminate the call.

### Memory

The MFC-7225N has dynamic memory and we have removed the factory-installed battery (used to hold the memory when the power goes out). In this way, unwanted image data can be removed from memory simply by turning the power off to the fax. The power switch is on the right side of the unit in the lower-rear corner. In addition, the 90si was specifically designed as a secure fax product and as such, does not retain any image data.

### Free Assistance and Technical Help

#### Technical Support:

You get Free, Unlimited, Lifetime, Technical Support with your purchase. Feel free to contact me for any reason...or you may call our Secure Fax Test Line (see below).

#### Secure Fax Test Line:

You may also test your system or any of those in your secure fax network with our Secure Fax Test Line. Test, troubleshoot or simply practice, as much as you wish, from 9AM to 6PM EST, Monday through Friday. We are equipped with STU-III's and get your operational quickly. Please call toll-free: **1-877-951-9814** or 336-697-9100. Lonnie Burns will answer and be able to help!

...or...

email to [help@gwfs.com](mailto:help@gwfs.com)

or visit our web site at <http://www.gwfs.com> and follow the link to "Technical Help."



GateWay  
Fax  
Systems, Inc.

GateWay Fax Systems, Inc.  
Virginia, USA

Toll Free: 1-877-951-9800

Tel: 804-796-1900, Fax: 804-796-1116

Web: <http://www.gwfs.com>

Email: [info@gwfs.com](mailto:info@gwfs.com)