

## 90si User's Guide Addendum for the Model 490 Secure Fax System (Possio PM80 and 90si)



### Set Up your Possio PM80

1. Plug the Trumpcard "Five of Diamonds" Modem Card into the slot on the bottom of the PM80 so that you can see the five of diamonds image.
2. Connect the phone cord between the Modem Card and the FAX jack on the 90si. Choose a 90si configuration in the **Easy-Fax 90si Secure Facsimile Gateway User's Guide** detailed in **Section 2.0 Installation**.
3. Connect the PM80's power supply to 110-240 VAC, 50-60 Hz power and to the power connector on the left side of the PM80.
  - a) The green Power Status (ac cord) light will blink and then come on solid.
  - b) The red Temporary Wait (packman) light will blink and then extinguish.
  - c) The red Battery Status (battery) light will illuminate, blink or extinguish, depending on the charge status of the battery.
  - d) The green Communications Status (double arrow) light will begin to blink.
4. The PM80 is now ready to operate.

### Erasing the PM80's Document Memory

1. Press the red Stop (triangle in circle) button for at least two seconds.
- Note. The document memory will be automatically erased if you do not attempt to send the document within two hours. Also, document memory is automatically erased following a successful transmission.

*(continued)*



GateWay  
Fax  
Systems, Inc.

GateWay Fax Systems, Inc.  
Virginia USA  
Tel: 804-796-1900, Fax: 804-796-1116  
Toll Free: 1-877-951-9800  
Web: [www.gwfs.com](http://www.gwfs.com)  
Email: [info@gwfs.com](mailto:info@gwfs.com)

### **90si User's Guide Changes**

The following 90si User's Guide sections, 3.3 and 3.4, have been modified specifically for the Possio PM80. All other sections of the 90si User's and Reference Guides remain unchanged.

#### **3.3 Sending a Secure Facsimile**

1. Place a call on your STU-III or STE.
2. Place the STU/STE in secure data mode.
3. Scan all the pages of your document, one page at a time, face down.
4. Press "1" and then the large, green Start (line in diamond) button.

#### **3.4 Receiving a Secure Facsimile**

1. Answer your STU/STE.
2. Place the STU/STE in secure data mode. The sender usually initiates this.
3. Standby, the fax will be received automatically.

### **For Assistance or Technical Help**

Call, toll free, 1-877-951-9800  
email to [help@gwfs.com](mailto:help@gwfs.com)  
or visit our web site at <http://www.gwfs.com>



**GateWay  
Fax  
Systems, Inc.**

**GateWay Fax Systems, Inc.**  
Virginia USA  
Tel: 804-796-1900, Fax: 804-796-1116  
Toll Free: 1-877-951-9800  
Web: [www.gwfs.com](http://www.gwfs.com)  
Email: [info@gwfs.com](mailto:info@gwfs.com)